

**8051-Based MCU**



---

---

# **CGH021A**

# **Data Sheet**

***8Bit Single-Chip Microcontroller***  
***Embedded 40V 3-Phase Gate-Driver***

**Version: 0.0**

## Features

### Motor Driving Engine (MDE)

- Space Vector PWM (SVPWM)
- Supports Sine-Wave and Square-Wave Solutions
- Supports Hall Latch Input
- Supports Digital OCP and Analog OCP (Over Current Protection)
- Programmable Dead Band
- Programmable Angle Shift Control (-59° to 59° in 128 steps)
- Frequency Generator (FG)

### Gate Driver

- Integrated 40V 3-phase P/N MOSFET Pre-driver
- Shoot-through protection
- Built-in 5V LDO

### Embedded MCU

- MCS<sup>®</sup>-51 Compatible
- 1T 8052 Central Processing Unit
- 4.5V to 5.5V Operation Range
- 4 Level Priority Interrupt
- 13 Interrupt Sources
- 1 External Interrupts (INT1N)
  - 2 External Interrupts (INT0N, INT1N)
  - 2 External OCP Interrupts (AOCP, OCP)
- Memory Size:
  - 8KB Flash Program Memory
  - 256 x 8-bit IRAM
  - 512 x 8-bit XRAM
- Up to 25 General-Purpose Input / Output (GPIO) Pins
- Three 16-bit Timer/Counters
- Watchdog (WD) Timer
- 8CH 10-bit ADC & 1CH 10-bit DAC
- Full Duplex UART Serial Channel
- Fast Multiplication-Division Unit (MDU):  
16\*16,32/16, 16/16, 32-bit L/R shifting and 32-bit normalization

## List of Contents

Features.....	2
List of Contents .....	3
1. Description .....	7
2. Block Diagram .....	7
3. Pin Assignments .....	8
3.1 Package Instruction SSOP28W (209mil).....	8
3.2 Package Instruction QFN40-5X5mm .....	9
4. Pin Definitions.....	10
5. Absolute Maximum Ratings .....	12
6. D.C. Characteristics .....	12
7. A.C. Characteristics .....	15
8. OPA Characteristics .....	16
9. A/D Converter Characteristics.....	17
10. Special Function Registers (SFR) .....	19
10.1 SFRs Memory Map.....	19
10.2 CGH021A SFRs and Reset Value .....	20
11. Memory.....	24
11.1. Program Memory.....	24
11.2. Data Memory .....	24
11.2.1 Data Memory (IRAM)(00H~FFH).....	24
11.2.2 Data Memory (XRAM)(F000H~FOFFH).....	25
12. Instruction Set .....	26
13. MCU .....	30
13.1 8051 Engine.....	30
13.1.1 ACC (Accumulator) .....	30
13.1.2 B (B Register).....	30
13.1.3 PSW (Program Status Word Register) .....	31
13.1.4 SP (Stack Pointer).....	32
13.1.5 DP0 (Data Pointer 0) .....	32
13.1.6 DP1 (Data Pointer 1) .....	33
13.1.7 AUX (Auxiliary Register) .....	34
13.1.8 RCON (Internal RAM Control Register) .....	34
13.2 GPIO .....	35
13.2.1 Port.....	35
13.2.2 PINCONG (Pin Configure Register).....	36
13.2.3 PINSET (Pin I/O Setting Register) .....	39
13.3 Clock Structure.....	41

13.4 Timer.....	42
13.4.1 PFCON (Peripheral Frequency Control Register).....	43
13.4.2 TMOD (Timer 0/1 Mode Register) .....	44
13.4.3 TCON (Timer 0/1Control Register) .....	45
13.4.4 T2CON (Timer2 Control Register) .....	46
13.4.5 Timer0 Mode 0 .....	47
13.4.6 Timer0 Mode 1 .....	47
13.4.7 Timer0 Mode 2 .....	47
13.4.8 Timer0 Mode 3 .....	48
13.4.9 Timer1 Mode 0 .....	48
13.4.10 Timer1 Mode 1 .....	48
13.4.11 Timer1 Mode 2 .....	49
13.4.12 Timer2 Mode 0 .....	49
13.4.13 Timer2 Mode 1 .....	49
13.4.14 Timer2 Mode 2 .....	50
13.4.15 Timer2 Mode 3 .....	50
13.5 Watchdog Timer .....	51
13.5.1 WDTC (Watchdog Timer Control Register) .....	52
13.5.2 TAKEY (Time Access Key Register).....	53
13.5.3 WDTK (Watchdog Timer Refresh Key) .....	53
13.6 Serial Port (UART).....	54
13.6.1 SCON (Serial Port Control Register) .....	56
13.6.2 SBUF (Serial Port Data Buffer).....	58
13.6.3 SREL (Serial Port Reload Register).....	58
13.7 Power Management.....	59
13.7.1 STOP MODE.....	59
13.7.2 IDLE MODE .....	59
13.8 Reset.....	60
13.8.1 RSTS (Reset Source Register).....	60
13.9 Interrupt Controller.....	61
13.9.1 IEN0 (Interrupt Enable Register 0) .....	63
13.9.2 IEN1 (Interrupt Enable Register 1) .....	64
13.9.3 IRCON1 (Interrupt Request Register 1) .....	65
13.9.4 IP (Interrupt Priority Register).....	65
14. 10-bit Analog-to-Digital Converter (ADC) .....	67
14.1 ADCCONT (ADC Control Register) .....	68
14.2 ADCSTR (ADC Start Convert and Setting Register).....	69
14.3 ADCD1 (ADC Data Register 1).....	69
14.4 ADCD2 (ADC Data Register 2).....	69

15. General PWM (GPWM) .....	70
15.1 GPWMCONT (General PWM Control Register) .....	71
15.2 GPWMMAX (General PWM Max Register) .....	71
15.3 GPWMDY (General PWM Duty Register) .....	72
16. Capture.....	73
16.1 CAPCONT (Capture Control Register).....	74
16.2 CAPT (Capture Total Count) .....	75
16.3 CAPH (Capture High-level Count) .....	75
17. Addition and Subtraction Unit (ASU) .....	76
17.1 AS_MD_CONT (ASU and MDU Control Register) .....	77
17.2 ASUD1 (ASU Data 1) .....	77
17.3 ASUD2 (ASU Data 2) .....	78
17.4 ASUR (ASU Result Register).....	79
18. Multiplication and Division Unit (MDU).....	80
18.1 AS_MD_CONT (ASU and MDU Control Register) .....	80
18.2 MD_CONT (MDU Control Register).....	81
18.2.1 MDEF.....	81
18.2.2 MDOV.....	82
18.3 MD0 – MD5 (Multiplication Division Register) .....	82
18.4 MDU Operation Description .....	83
18.4.1 Loading the MDx registers .....	83
18.4.2 Executing calculation .....	84
18.4.3 Reading the result from the MDx registers.....	84
18.4.4 Shifting .....	85
18.4.5 Normalizing.....	85
19. Motor Driving Engine (MDE).....	86
19.1 HALL Interface Processor .....	87
19.2 Motor Speed Observer.....	89
19.3 Motor Angular Position Detection.....	92
19.4 Sinusoidal Data ( LUT ) .....	97
19.5 Motor Drive Signal Generator.....	97
19.6 SVPWM Engine.....	99
19.6.1 SVPWM Engine Architecture .....	99
19.6.2 SVPWM Current Drive.....	99
19.6.3 Motor PWM Output Setting.....	102
19.7 OCP Protection (Over Current Protection).....	109
19.7.1 OCP Block Architecture .....	109
19.7.2 OCP Block description and setting .....	109
19.8 MDE SFR List.....	113

19.8.1 MCONT1 SFR .....	113
19.8.2 MCONT2 SFR .....	114
19.8.3 MCONT3 SFR .....	114
19.8.3 HALLDBT (Hall De-bounce Time Register) SFR.....	114
19.8.4 HALLSET (Hall Setting Register 1, 2, 3) SFR .....	116
19.8.5 HALLST (Hall Status Register) SFR .....	116
19.8.6 ROTORSPEED (Rotor Speed Count Register) SFR .....	117
19.8.7 VRHALL (Virtual Hall Register) SFR.....	117
19.8.8 MPWM_CYC (Motor PWM Cycle Register) SFR .....	118
19.8.9 MPWMDY (Motor PWM Duty Register) SFR.....	119
19.8.10 MIN_DUTY (Minimum Duty Limit Register) SFR.....	120
19.8.11 MPWMDT (Motor PWM Dead-Time Register) SFR .....	120
19.8.12 MPWMCONT1 (MPWM Control Register 1) SFR .....	120
19.8.13 MPWMCONT2 (MPWM Control Register 2) SFR .....	121
19.8.14 MPWMINV (MPWM Inverse Selection Register) SFR .....	122
19.8.15 SVPWMAMP (SVPWM Amplitude Register) SFR .....	123
19.8.16 SVPWMAMPFT (SVPWM Amplitude Fine-Tune Register) SFR.....	123
19.8.17 SVPWMANG (SVPWM Angular Register) SFR .....	123
19.8.18 AS (Angle Shift Control Register) SFR.....	124
19.8.19 Over Current Protect (OCP) SFR.....	125
19.8.20 Analog Over Current Protect (AOCP) SFR.....	126
19.8.21 IMPMISC_KEY (IMPROVE Miscellaneous Function Turn On Key) SFR .....	126
19.8.22 IMPMISC_FUN (IMPROVE Miscellaneous Function Setting) SFR.....	127
19.8.23 ONE_HALLSET (One Hall Setting) SFR .....	128
19.8.24 FG_CTRL (Frequency Generator Control) SFR.....	129
19.9 SYNC .....	130
20. Typical Application Circuit.....	131
21. Package Information .....	132
21.1 SSOP28W 209mil (WL28) Outline Dimensions .....	132
21.2 QFN40-5x5x0.75 mm (AY40) Outline Dimensions .....	133
22. Marking Distinguish .....	134
22.1 Standard Ink (w/o code).....	134
22.2 Customization Ink (with customization code).....	135
23. Ordering Information .....	136
23.1 Standard Product Name.....	136
23.2 Customization Product Name .....	136
<b>24. Revision History .....</b>	<b>137</b>

# 1. Description

The CGH021A is a 3-phase BLDC motor controller which embedded 3-phase 40V P/N gate-driver and supports the hall-latch interfaces. The CGH021A supports both the six-phase-drive for torque intensive application and sine-wave-drive to effectively suppress motor vibration and with the built-in, innovated speed control mechanism; an ultra-high RPM can be achieved.

The OCP protection circuitry to prevent motor damage and enhance system reliability is built-in as well. The block diagram is shown in Figure 2.1

# 2. Block Diagram






Figure 2.1 CGH021A BLDC motor controller block diagram

### 3. Pin Assignments

#### 3.1 Package Instruction SSOP28W (209mil)



### 3.2 Package Instruction QFN40-5X5mm



## 4. Pin Definitions

Table 4.1 Pin Definitions

SSOP28W PIN N.O.	QFN40 PIN N.O.	Name	Type	Description
27	32	VCC	Power	Supply voltage input.
1	33	UH	O	High side phase-U PMOS driver.
2	34	UL	O	Low side phase-U NMOS driver.
3	35	VH	O	High side phase-V PMOS driver.
4	36	VL	O	Low side phase-V NMOS driver.
6	37	WH	O	High side phase-W PMOS driver.
5	38	WL	O	Low side phase-W NMOS driver.
24	26	VCC_LDO	Power	LDO 5V power supply.
25	27 / 28	LDO_5	Power	5V output of LDO.
28	30	PGND	Ground	Power ground.
26	31	VCC_8	O	LDO VCC_8 output
--	29 / 39	SGND	Ground	Logic ground
7	1	RSTN	I	System Reset.
--	18	CH7	I	Analog Input Ch7.
		CAP2	I	Capture Input 2
		P2.7	I/O	Bit 7 of Port 2.
--	17	CH6	I	Analog Input Ch6.
		P2.6	I/O	Bit 6 of Port 2.
--	16	CH5	I	Analog Input Ch5.
		P2.5	I/O	Bit 5 of Port 2.
8	15	CH4	I	Analog Input Ch4.
		P2.4	I/O	Bit 4 of Port 2.
9	14	CH3	I	Analog Input Ch3.
		FG	O	Frequency Generator Output
		P2.3	I/O	Bit 3 of Port 2.
12	2	RX	I	Serial Data Transmit (UART)
		P3.0	I/O	Bit 0 of Port 3.
13	3	TX	O	Serial Data Receive (UART)
		P3.1	I/O	Bit 1 of Port 3.
14	4	SDA <sub>ICE</sub>		For ICE (In Circuit Emulator).
15	5	SCL <sub>ICE</sub>		For ICE (In Circuit Emulator).
17	8	VDD5	Power	5.0V Voltage Input. A 0.1uF and 10uF (minimum)

				capacitor should be connected between this pin and VSS.
18	9	V18	O	1.8V Voltage Output. A 0.1uF and 1uF (minimum) capacitor should be connected between this pin and VSS.
19	10	VSS	Ground	Power Ground.
11	11	CH0	I	Analog Input Ch0.
		CAP1	I	Capture Input 1
		GPWM	O	General PWM output.
		P1.6	I/O	Bit 6 of Port 1.
--	12	CH1	I	Analog Input Ch1.
		INT0N	I	External Interrupt 0. Low level trigger or falling edge trigger.
		P3.2	I/O	Bit 2 of Port 3.
10	13	CH2	I	Analog Input Ch2.
		INT1N	I	External Interrupt 1. Low level trigger or falling edge trigger.
		P3.3	I/O	Bit 3 of Port 3.
21	22	HWP	I	Hall Latch input positive input. (HALL W)
		P0.2	I/O	Bit 2 of Port 0.
20	23	HVP	I	Hall Latch input positive input. (HALL V)
		P0.1	I/O	Bit 1 of Port 0.
--	19	VOUT	O	OPA output
--	20	VINN	I	OPA input (-)
--	21	VINP	I	OPA input (+)
22	24	HUP	I	Hall Latch input positive input.(HALL U)
		P0.0	I/O	Bit 0 of Port 0.
23	25	OCPN	I	Over current protection. Active-low.
		P0.3	I/O	Bit 3 of Port 0.
16	6	XTALI	I	Crystal input pin. Connect the crystal 12MHz between this pin and XTALO and a 22pF capacitor to VSS.
		T1	I	TIMER1 External Input.
		P3.5	I/O	Bit 5 of Port 3.
--	7	XTALO	O	Crystal output pin. Connect the crystal 12MHz between this pin and XTALI and a 22pF capacitor to VSS.
		T0	I	TIMER0 External Input.
		P3.4	I/O	Bit 4 of Port 3.